

LED line PRIME

Code: 201217

EAN: 5905378201217

RF Wall Remote for VARIANTE RGB PRIME Controller

The RF LED line PRIME wall remote control for the VARIANTE RGB controller is a modern device that combines aesthetics with functionality. It allows wireless lighting control at the common 2.4 GHz frequency, providing a range of up to 20 metres. Thanks to the unique interface, the operation is intuitive and the possibility to group VARIANTE controllers increases the comfort of use.



5
WARRANTY

MAX
-20÷60°C

CE

Technical data

Parameter	Value	Parameter	Value
Warranty	5	Ambient temperature suitable for operation	-20÷60
Voltage	• 90-265 V AC	Length	34
Working power	<2	Width	86
RF frequency	2.4 GHz	Height	86
RF distance	≤20		


LED line PRIME

Code: 201217

EAN: 5905378201217

RF Wall Remote for VARIANTE RGB
PRIME Controller

Technical drawing




Light distribution

Additional product photos




Logistics data




Single packaging

Quantity	1
Width	34 mm
Height	86 mm
Length	86 mm
Weight	0,14 kg



Bulk packaging

Quantity	50
Width	230 mm
Height	190 mm
Length	480 mm
Volume	0,020 m3
Weight	7,35 kg
Comments	



Europallet

Height	1840 mm
Quantity in layer	400
Number of layers	8
Bulk quantity	3200
Weight	470,4 kg

LED line PRIME

Code: 201217

EAN: 5905378201217

RF Wall Remote for VARIANTE RGB
PRIME Controller

Example application