



LED line PRIME

Code: 201224

EAN: 5905378201224

RF wall remote for VARIANTE
RGBW/RGBCCT PRIME controller

The RF LED line PRIME wall remote control for VARIANTE RGBW/RGBCCT controller is a modern solution that combines functionality with aesthetics. High quality and robust design ensure long-term use. With a range of up to 20 m and 2.4 GHz radio frequency, the remote control enables precise lighting control. Easy pairing with controllers eliminates interference.



Technical data

Parameter	Value
Warranty	5
Voltage	• 90-265 V AC
Working power	<2
RF frequency	2.4 GHz
RF distance	≤20

Parameter	Value
Ambient temperature suitable for operation	-20÷60
Length	34
Width	86
Height	86


LED line PRIME

Code: 201224

EAN: 5905378201224

RF wall remote for VARIANTE
RGBW/RGBCCT PRIME controller

Technical drawing




Light distribution

Additional product photos




Logistics data




Single packaging

Quantity	1
Width	34 mm
Height	86 mm
Length	86 mm
Weight	0,14 kg



Bulk packaging

Quantity	50
Width	230 mm
Height	190 mm
Length	480 mm
Volume	0,020 m3
Weight	7,35 kg
Comments	



Europallet

Height	1840 mm
Quantity in layer	400
Number of layers	8
Bulk quantity	3200
Weight	470,4 kg

LED line PRIME

Code: 201224

EAN: 5905378201224

**RF wall remote for VARIANTE
RGBW/RGBCCT PRIME controller**

Example application