

LED line PRIME

Code: 201217

EAN: 5905378201217

**RF Wall Remote for VARIANTE RGB PRIME Controller**

The RF LED line PRIME wall remote control for the VARIANTE RGB controller is a modern device that combines aesthetics with functionality. It allows wireless lighting control at the common 2.4 GHz frequency, providing a range of up to 20 metres. Thanks to the unique interface, the operation is intuitive and the possibility to group VARIANTE controllers increases the comfort of use.



**Technical data**

Parameter	Value
Warranty	5
Voltage	• 90-265 V AC
Working power	<2
RF frequency	2.4 GHz

Parameter	Value
RF distance	≤20
Ambient temperature suitable for operation	-20÷60
Height	86


LED line PRIME

Code: 201217

EAN: 5905378201217

**RF Wall Remote for VARIANTE RGB PRIME Controller**

**Technical drawing**






**Light distribution**

**Additional product photos**



**Logistics data**



**Single packaging**

Quantity	1
Width	34 mm
Height	86 mm
Length	86 mm
Weight	0,14 kg

**Bulk packaging**

Quantity	50
Width	230 mm
Height	190 mm
Length	480 mm
Volume	0,020 m3
Weight	7,35 kg
Comments	

**Europallet**

Height	1840 mm
Quantity in layer	400
Number of layers	8
Bulk quantity	3200
Weight	470,4 kg

---

LED line PRIME

Code: 201217

EAN: 5905378201217

**RF Wall Remote for VARIANTE RGB  
PRIME Controller**

---

**Example application**