

LED line LITE

Code: 201019

EAN: 5905378201019

**DOWNLIGHT MOLLY 4000K 18W 1900lm
round IP20 White LITE motion sensor**



The LED line LITE Downlight MOLLY 18W 1900lm 4000K with motion sensor is a modern lighting solution that provides efficient and even illumination. It offers a power of 18W, with a luminous flux of 1900lm, resulting in a luminous efficiency of 105 lm/W.

It features a color temperature of **4000K** for a natural light effect and an ingress protection class of **IP20**.

The product made of high-quality polycarbonate guarantees durability and aesthetics.



Technical data

Parameter	Value
Energy efficiency class 2019/2015	D
Warranty	3
Power	• 18 W
Voltage	• 170-260 V AC
Correlated colour temperature	• 4000 K
Colour of the light	White
Colour rendering index Ra	80
IP protection rating	IP20
IEC protection class	II
Luminous efficacy	105
Luminous flux	1900
The lumen maintenance factor	96
Lifetime L70B50	30 000 h
Survival factor	0.9
Colour consistency in McAdam ellipses	≤6

Parameter	Value
Frequency of the supply voltage	50/60Hz
Beam angle	110
Sensor type	Microwave
LED type	SMD LED 2835
LED quantity	60
Power Factor	0,5
Number of on/off cycles	20000
Ambient temperature suitable for operation	-20÷40
For indoor use	Inside
Mounting hole diameter	140-160
Height	26
Fixture's diameter	170 mm
Colour	White
Material (housing)	Polycarbonate


LED line LITE

Code: 201019


EAN: 5905378201019

**DOWNLIGHT MOLLY 4000K 18W 1900lm
round IP20 White LITE motion sensor**

Technical drawing





Light distribution



Additional product photos



Logistics data



Single packaging

Quantity	1
Width	178 mm
Height	38 mm
Length	176 mm
Weight	0,187 kg

Bulk packaging

Quantity	60
Width	390 mm
Height	374 mm
Length	551 mm
Volume	0,080 m3
Weight	12,2 kg

Europallet

Quantity	1200
Height	1,9 m
Quantity in layer	240
Number of layers	5
Bulk quantity	20
Weight	274 kg

LED line LITE

Code: 201019

EAN: 5905378201019

**DOWNLIGHT MOLLY 4000K 18W 1900lm
round IP20 White LITE motion sensor**

Example application

