

LED line PRIME

Code: 471338

EAN: 5907777471338

RF remote for VARIANTE RGB/RGBW controller



The RF LED line remote control for the VARIANTE RGB/RGBW controller is an advanced device that allows precise lighting control. It works on 2.4 GHz frequencies, offering a range of up to 20 metres. It is powered by three AAA batteries (included in the set) and its functionality includes the possibility to group controls of as many as four zones and choose from eight dynamic modes and six colours. Additionally, the wall handle provides easy installation.



Technical data

Parameter	Value
Warranty	5
Voltage	• 3 V 2*AAA DC
IP protection rating	IP20
Standby power	54
Working power	75
RF frequency	2.4 GHz
RF distance	20

Parameter	Value
Number of zones	4
Standby current	<18
Working current	<25
Ambient temperature suitable for operation	-20÷60
For indoor use	Inside
Height	20 mm


LED line PRIME

Code: 471338

EAN: 5907777471338

RF remote for VARIANTE RGB/RGBW controller

Technical drawing






Light distribution

Additional product photos



Logistics data



Single packaging

Quantity	1
Width	150 mm
Height	36 mm
Length	51 mm
Weight	0,11 kg

Bulk packaging

Quantity	100
Width	320 mm
Height	280 mm
Length	380 mm
Volume	0,034 m3
Weight	11,35 kg
Comments	

Europallet

Quantity	4000
Height	1,8 m
Quantity in layer	800
Number of layers	5
Bulk quantity	40
Weight	479 kg

LED line PRIME

Code: 471338

EAN: 5907777471338

**RF remote for VARIANTE RGB/RGBW
controller**

Example application